

# iTrainer dog training collar iT728

## Components



- Charger
- USB Cable
- Contact Points
- Test Bulb
- Receiver Collar
- Remote Transmitter
- Adjustable TPU Belt

## Key Definition



1. Antenna

2. Led light

3. LED Indicator

4. 1/2 Dog Channels (Channels for 1 or 2 dog)

5. Light Button

6. 1 dog mode LED indicator

7. 2 dog mode LED indicator

8. 1-7 levels correction



9. Beep Button



10. Vibration Button



11. Shock Button

12. Charging hole

1. Antenna: Transmit the signal to receiver collar
2. Led light: This light will be on/off when press LED light button for 3 seconds.
3. LED Indicator: When charging, the light will flash and will be on still after fully charged. Press any button, the light will flash to indicate the transmitter is working.
4. 1/2 Dog Mode button: Press the 1/2 button for the first time, the left blue light is on to indicate that it is in 1 dog mode. Press the button again, the right blue light is on to indicate that it is in 2 dog mode. Press the button for the third time, both of the blue lights are on to indicate that it is in working mode for two dogs.
5. Light Button: Press this button for 3 seconds to turn on/off the LED light.
6. 1 dog mode LED indicator: When it is on, it indicates the transmitter is controlling the first receiver collar.
7. 2 dog mode LED indicator: When it is on, it indicates the transmitter is controlling the second receiver collar.
8. 1-7 levels correction. From 1 to 7 levels, the intensity range from the weakest to the strongest.



1. Contact Points:
2. Rubber Cover
3. Charging holes
4. On/Off Button
5. LED Red Indicator
6. LED Blue Indicator

Contact Points: Deliver the safe shock correction

Charging holes: Charge for receiver collar

Rubber Cover: seal charging hole to keep from dust.

On/Off Button: Press the button for 3 seconds to turn on/off the receiver collar.

LED Red Indicator: When the receiver is connected to the outlet, charging, the Red Indicator shows up to indicate the charging status. When the receiver is turned on, the Red light flash 2 times one second to indicator it is in low power. While the Red light shows up to indicator the encoding status. After encoding completed, the Red light flash two times and turn off.

LED Blue Indicator: When the receiver is fully charged, the Blue Indicator shows up. After the encoding completed, the Blue flash every 10 seconds.

**Features:**

- 1.LED Indicator.
- 2.300m Remote control distance.
- 3.Waterproof receiver collar.
- 4.The system can expandable to 2 receiver collar.
- 5.Rechargeable remote transmitter and receiver collar.
- 6.1-7 levels adjustable shock vibration and beep by rotating the thumbwheel.
- 7.Led Light.Turn on/off the light by pressing the light button for 3 seconds.
- 8.Tone Indicator.  
Press any button of the transmitter,it produces B sound.  
If press the shock button more than 10 seconds,it would produce “BBB” warning sound.
- 9.Power Saving:  
Both of the transmitter and receiver can be turned off manually.  
The Remote Transmitter will go into Standby Mode if no operation for 2 minutes.  
Press any button will activate the transmitter.  
In Standby Mode,the receiver will flash blue light every 10 seconds.
- 10.Two pairs of metal prong(short/long) to suit dogs with varied fur thickness.

**How the iTrainer Rechargeable and waterproof Remote Dog Training System Works**

This dog training system has been proven safe,comfortable,and effective with 550 meters remote range for all dogs over 8 pounds.It includes the remote transmitter and receiver collar. The collar is worn on dog’ s neck and controlled by the remote transmitter.

Press a button of the remote transmitter,it will send a signal,activating the receiver collar.

The collar can produce adjustable Vibration,discharge shock,BB Tone lighting etc.Using this training system consistently and correctly,many misbehaviors of your dog’s can be corrected and any basic obedience commands can be taught.

**Note:**This training system has a range up to 550m.Depending on the way you hold the remote transmitter,the range may vary.Hold the remote transmitter in a horizontal position away from your body to achieve optimum range.Terrain,weather,vegetation,transmission from other radio devices,and other factors will affect the range of your remote trainer.

**Operating Guide****Step 1 Check the battery of the transmitter and receiver**

Transmitter : Turn on the remote transmitter by pressing any button..If cannot be turned on,it means that it is in low power and need charging.

Receiver Collar: Turn on the receiver collar by pressing the ON/OFF button.If the Red LED light is on ,it means it has enough power.If red LED light flashes 2 times a second or cannot be on,it means that it is in low power and need charging.

**Step 2 Charging the transmitter and receiver.**



Connect the charger connector to the charging hole and put the charger into a standard outlet. The Red LED light will be on when it begins charging. Please charge the transmitter and receiver up to 4 hours for the first charging. After fully charged, the BLUE LED light will be on.

### **Step 3 Connect/Encode the transmitter with the receivers.**

- a. Turn on the receiver.
- b. Adjust the thumb knob on the transmitter to any levels **Except 0** Level.
- c. Press any button on the transmitter, the connection between the transmitter and the receiver is succeeded.

**Note:** If it is 1-2 system, please connect the transmitter with the receivers one by one.

Don't turn on two receivers at the same time to avoid encoding the two receivers at the same channel.

### **Step 4 Check the Functions of Shock, Vibration, Beep and Lighting.**

Rotate the thumbwheel dial to any levels except "0"

Press the Beep or Vibration button, the receiver will produce beeping sound or vibration.

To test the shock function, cap the shock test kit on the metal prongs, press the shock button to see the bulb light up immediately.

To test the Lighting, press the light button on the right side of the transmitter for 3 seconds, the lamp will light up. Press the light button for 3 seconds, the lamp will turn off.

### **Step 5 Adjust the intensity/levels of the functions.**



Rotate the thumbwheel dial to choose the desired levels of correctional signals.

**Note:** 1 level is the weakest level, 7 level is the levels strongest.

### **Step 6 Start to Train**

Put the collar into the receiver, wear the receiver around the dog's neck. Please leave about one finger distance between the collar and the neck.

Press the 1/2 dog channel button to choose the dog Mode. The left blue indicator means to train the 1<sup>st</sup> dog, the right blue indicator means to the 2<sup>nd</sup> dog. Both of the two blue indicators mean to train 2 dogs at the same time.

#### **Training tips:**

This product is intended to support behavioral training and is not designed to be used without necessary verbal/non-verbal interaction.

Always praise your dog for good behavior. Verbal commands combined with positive reinforcement will contribute to the success of your training and will achieve the fastest, most desirable results.

The recommended age for dog training is a minimum of 6 months, provided that dog has the attention span and capability to learn basic commands.

Work with your pet on one behavior at a time to avoid confusion and frustration. Use as little stimulus as possible and only to reinforce verbal commands when necessary. Do not over correct your dog!

Use the beeps as warning by pressing the Ultrasound button. The dog will become conditioned to the beep preceding the corrective stimulus and will soon learn to recognize the beep as a warning to along with your verbal command.

This system is not appropriate for correcting aggressive behavior. Please consult a professional trainer for advice.

Use the corrective stimulus, along with your verbal command, to deter the dog from undesirable behavior by administering the stimulus DURING THE ACTUAL BEHAVIOR. Using the device as punishment after the fact is not recommended and may serve to confuse and frustrate the animal.

Do not solely rely on this product to train your dog. If your dog shows signs of growling, snarling, biting or aggression while using the collar, discontinue use immediately and contact a professional trainer.

Some dogs will not respond to this product. We cannot guarantee the effectiveness of this or any trainer for your dog.

This product is not recommended for aggressive, elderly animals in poor health, or animals otherwise unable to withstand the stimulus.

## **Safety**

To maximize the effectiveness of the iT728 remote training system, and safety of your dog, check the fit of the collar frequently and readjust the position of the electrodes on the animal's neck, checking for signs of irritation or discomfort.

If signs of skin irritation are noticed, immediately discontinue use and apply antibiotic ointment to help heal and soothe the area. If the condition persists beyond 48 hours, please ask for advice of a veterinarian. Such side effects are extremely rare and are generally caused by a more serious condition.

The collar is not intended to be left on a dog for extended period of time without supervision and doing so can lead to health problems. The conservative recommended time limit without supervision is 12 hours.

Wash the dog's neck area and the correction poles as often as needed to keep the area and poles clean. Make sure the straps are clean for best performance. The straps can be removed for cleaning but must be replaced in the same position.

From undesirable behavior by administering the stimulus during the actual behavior, using this device as a punishment after the fact is not recommended and may serve to confuse or frustrate the animal.

## **Common Problem & Fixes:**

### **The receiver does not seem to be working properly:**

#### **No beep,vibration or shock**

- Make sure the receiver is fully charged.Low charge will cause the receiver to work inconsistently.
- Follow the instruction,match the receiver to the transmitter.
- Make sure the transmitter battery is good.A low battery will disallow the remote to emit a strong signal every time.
- Make sure the thumb knob on transmitter is NOT pointing at a ZERO level.
- Make sure the receiver is turned on.If the receiver is turned off,the transmitter will not be able to send out a signal and the signal icon light will not flash accordingly.

#### **The receiver does not seem to take a charge:**

- Make sure the charger had been plug into the main supply tightly,as well as the charging end had plug into the charging hole tightly,in charging the red LED light inside receiver should come on.

### **My dog does not respond when I issue a correction:**

- Test the receiver according to the instructions above to make sure each stimulus is functioning.
- Make sure the correction prongs are positioned properly and that both prongs are making contact with the dog's skin and the collar is snug.
- Increase the intensity level of the correction.

## **Safety Guidance**

- It is forbidden to open the shell in case of breakage of the machine or harm the waterproof feature.Otherwise, it will violate warranty rules.
- In order to guarantee submersible feature,the waterproof rubber charging lid should be plugged in tightly.
- Only use the supplied adaptor to charge the receiver,otherwise the receiver will probably be damaged.
- Users are not suggested to touch the shocking prongs,otherwise the receiver will harm human body in case of shocking operation,for shocking test,please use the supplied test kit.
- If there has water in the charging hole,please dry it before charge the receiver.



## **Warranty, Term & Condition, Compliance**

We guarantee the original retail purchaser that the iTrainer iT728 Remote Training System will be free from defects in material and workmanship for a period of one year from the date of the original retail purchase. Provided that the damage is not caused by abnormal use or neglect. Warranty does not cover lost parts, cracked screen, physical damage or water damage. Warranty may include repair or exchange. After expiration of the warranty, replacements and repairs are available at an additional repair charge.

## **Additional Information for Terms of Use and Limitation of Liability**

### **1. Terms of Use**

It is understood that you accept without modification of the terms and conditions, the offering to you of this product.

### **2. Proper Design and Use**

This training collar had been designed for the training of dogs. Your pet's temperament may not be suitable for this system. This collar is not recommended for dogs that are aggressive or neglected.

### **3. Unlawful and Prohibited Use**

This product is designed for training purposes. It is not intended to punish, injure, provoke or harm. Using this product in a way in which is not intended is strictly prohibited and can result in violation of Federal, State or local laws.

### **4. Limitation of Liability.**

In no event should we be liable for any damages arising out of or connected with the use or misuse of this product. Buyer assumes all risks and liability associated with the use of this product.

### **5. Modification of Terms and Conditions**

We reserves the right to change the terms and conditions under which this product is offered. This equipment is in full compliance with the limits for Class B digital device, pursuant to Part 15 of the FCC rules in the United States and Canadian ICES-003 regulations. For Europe, this product meets the standards for R&TTR-Directive 1195/05EEC compliance.

In some countries, this device may be restricted according to frequency or transmission regulations: the user is responsible for compliance.

Unauthorized changes or modifications to the equipment are not approved by us, and are additionally in violation of FCC regulations. Such modifications render the warranty immediately void.

### Additional Information

Common size of different dogs				
Size	Neck(cm)	Chest Measurement(cm)	Back Length(cm)	Type
Mini	20-22	25-30	19	Chihuahua, Yorkshire Terrier
Small	20-24	29-36	23	Chihuahua, Yorkshire Terrier, Poodle, Pomeranian
Medium	23-28	35-42	28	Maltese Schnauzer, Pekingese
Large	27-31	41-47	31	Schnauzer, English Cocker Spaniel
Large	30-34	46-53	35	Beagle
Large	33-37	52-59	40	Husky
Huge	43-48	76-84	60	Labrador Retriever
	47-52	88-97	65	Golden Retriever, Old English Sheepdog
	52-62	92-100	70	

### Common weight of dogs

Large Dog (Body height above 61 cm, Weight above 40 kg)

Medium Dog (Height 40.7-61cm, Weight 11-30 kg)

Mini Dog (height under 25cm, Weight under 4kg)